







0123

TÜV SÜD Product Services GmbH Ridlerstraße 65 ° 80339 Munich ° Germany



www.medrx-diagnostics.com



1200 Starkey Rd., #105, Largo, FL 33771 U.S.A. Toll Free: (888) 392-1234 • (727) 584-9600

Fax: (727) 584-9602 • Email: medrx@medrx-diagnostics.com



MedRx's Authorized Representative in Europe DGS Diagnostics A/S Audiometer Alle 1 • 5500 Middelfart • Denmark



MedRx's Archived manuals are available at www.medrx-diagnostics.com/support/manuals-studio-software/archive

Contents

Computer Requirements	4
Software Installation	5
Connecting Device	7
Sound Card Settings	8
Connecting to a Database	10
Complaints/Safety Reporting	
Limited Warranty	





Computer Requirements

MedRx Minimum Computer Specs:

Windows® - PC compatible computer Intel™ i5 2.0 GHz or better 4 GB RAM 20 GB free hard drive space Available 2.0 USB port Windows 10 or 11 Professional Compatible with 3.0 USB

MedRx Recommended Computer Specs:

Windows® - PC computer Intel™ i5 Quad Core or better 8 GB RAM or more Available USB 3.0 Graphics adapter with 2GB dedicated video memory 50 GB or more free hard drive space High speed internet connection Windows 10 or 11 Professional Compatible with 3.0 USB


Software Installation



- 1. Insert the MedRx USB Flash Drive into a USB port:
 - Launch My Computer
 - Locate USB Drive



(E:) may vary depending on the USB port selected. Consult your computer's documentation.



2. Double click on **Setup** to launch:

NOTE: If requested, Accept Permission to Install Software.




3. On the Setup screen, choose Install MedRx Studio.



- This is the Welcome screen.
 - To continue, click Next.




- 5. Read the Software License Agreement. This important document defines the acceptable usage of the Studio Software.
 - After reading the agreement, select I accept...
 - Click Next.




- 6. This screen sets the language and location choice.
 - Make language selection and click **Next**.




- 7. This screen indicates the location of the program files. The default location is recommended for most users. If necessary, this location can be changed.
 - To continue with the default settings, click **Next**. NOTE: To change the location of the files (advanced users or system administrators only, click Change).



- 8. Installation of Program is ready to start.
 - To continue, click Install.
 - To make changes, click Back.



9. Installation is in process.




- 10. When the installation is complete.
 - Click Finish.

Connecting Device


Your MedRx products are USB powered.

Connect the USB cable from the MedRx device to your computer.





Wait for the system to copy and install default Windows drivers.



When this screen appears, and all devices are "Ready to use".


Click Close.

Sound Card Settings

Next you need to confirm or set the default Windows sound card settings. This will route all non-MedRx Windows sounds to the internal sound card of your computer. (These sounds include event notifications such as new e-mail and error warnings as well as audio and video playback.)



1. **Right click** the speaker icon in your system tray.




2. Select the **Sounds** option from the list.



3. In the Windows Sound control panel, under the Playback tab and the Recording tab, make sure the MedRx Audio Device is not set as default. If it is default, change this by clicking on your system (non-MedRx) audio device and then choose Set Default.

NOTE: The internal sound card on your computer will likely not have the same name as this screen shot. Consult your computer's documentation for the name of the internal sound card and set this control accordingly.



4. In the windows sound control panel, in the Playback tab right click the MedRx device and select properties. Navigate to the Enhancements tab and Disable all enhancements. Then click Apply and Ok.

Enhancements may not be available on all PCs. This does not apply to any PC without audio enhancements.

5. In the windows sound control panel, in the **Recording** tab right click the MedRx device and select properties. Navigate to the Enhancements tab and click Disable all enhancements. Then click Apply and Ok.

Enhancements may not be available on all PCs. This does not apply to any PC without audio enhancements.

6. Click OK.


Congratulations you have set-up your new MedRx Device

Connecting to a Database

The MedRx Studio software can run with Noah Systems, OtoAccess, MS SQL Express, or without database access.



To set-up a Database, double click the MedRx Studio icon on your Windows Desktop.



If the Login window appears, click Login. There is no password set on initial installation.



Click the settings wheel in the top right menu bar.



Select Database from the tabs. Click on your desired Database. Close the MedRx Studio software to apply changes.

Note: Only databases that are set up will appear.

Database Set Up



Without a Database

Double click the MedRx Studio shortcut on your Windows Desktop.





Noah

- Download and install Noah.
- Launch Noah.
- Select a patient.
- Launch MedRx Studio module following Noah procedures.



OtoAccess

- Download and install OtoAccess.
- Launch OtoAccess.
- Select a patient.
- Launch MedRx Studio module following OtoAccess procedures.




MS SQL Express


- Download and install MS SQL Express.
- Run MedRx MS SQL database set up.

Double click the MedRx Studio shortcut on your Windows Desktop.

Note: MedRx provides access to SQL database connections. The database owner must configure the database and backup policies to meet local regulatory requirements.



Select Client in the top left corner.



- + Create client.
- Pencil Edit client.
- Trash Delete client.

Complaints/Safety Reporting

Please contact your local distributor in case of any incidents related to product defects (hardware defects or software bugs) or adverse events (which does not necessarily have a causal association to the product). It is recommended for a user to report all the known facts about the incident. Upon receipt of any serious incident with serious health impact for the patient or user (serious adverse events), local distributor shall report to MedRx through its appropriate vigilance system. MedRx shall ensure that the regulatory authority in patient's home country is informed according to the vigilance requirements. MedRx shall handle all the product complaints and adverse events as per the internal procedure.

Limited Warranty

MedRx, Inc warrants this product to be free from defects in material and workmanship for one year from the time of purchase. If this system fails to perform as specified during this period, the purchaser is responsible for calling MedRx at (888) 392-1234 or (727) 584-9600. The company's representative will advise the owner to either return specific components or the entire system to:

MedRx, Inc. 1200 Starkey Road #105 Largo, FL 33771 USA

MedRx will repair or replace any defective devices, fully test the system and/or components and ship the system promptly back to the owner. There is no cost for the repair or return shipping, provided the system is one year old or less and has not been misused, abused or damaged. Such damage includes, but is not limited to, dropping, exposure to excessive heat greater than 100°F and water/liquid damage.

Repair or replacement of the system as provided under this warranty is the sole and exclusive remedy of the purchaser. MedRx shall not be liable for any consequential or incidental damages or for breach of any express or implied warranty. Except to the extent of applicable law, any implied warranty, merchantability or fitness of this product is limited to the duration of this warranty.

MedRx will, at its discretion, service and repair out of warranty products at the purchaser's request, charging for parts and labor as necessary.

The limited warranty is deemed void if software or hardware is installed on this product which is not pre-approved by MedRx, Inc. Approved software includes Noah and HIMSA approved hearing aid manufacturer programming modules for fitting hearing aids.

MedRx, Inc. is not responsible for problems resulting from installation of unapproved software or hardware. In the event of unapproved software or hardware installed on the system causing a conflict, MedRx will service the product for a fee to be determined at the time of service.

Any extension of this warranty past the initial one-year warranty is subject to the following (where applicable).

- 1. A \$300 deductible per repair.
- 2. Extended warranty does not include cables, connectors, or peripherals.